


A Computational Biology Approach to Modelling and Identification of Human Physiology

Keynote Talk

Sunil L. Kukreja



Outline

- Introduction: System Identification
- Non-linear Model Form
- Identification Problem
 - Order Estimation, Parameter Estimation, Structure Detection & Model Validation
- System Identification for the Study of Human Biology
 - Modelling & Parameter Estimation Techniques for Human Biomechanics & Vestibulo-Ocular Dynamics
 - Structure Detection of Non-linear Systems for the Study of Human Ankle Dynamics
- Conclusions


Outline

- Introduction: System Identification
- Non-linear Model Form
- Identification Problem
 - Order Estimation, [Parameter Estimation](#), Structure Detection & Model Validation
- System Identification for the Study of Human Biology
 - [Modelling & Parameter Estimation Techniques for Human Biomechanics & Vestibulo-Ocular Dynamics](#)
 - Structure Detection of Non-linear Systems for the Study of Human Ankle Dynamics
- Conclusions


Outline

- Introduction: System Identification
- Non-linear Model Form
- Identification Problem
 - Order Estimation, **Parameter Estimation**, **Structure Detection** & Model Validation
- System Identification for the Study of Human Biology
 - **Modelling & Parameter Estimation Techniques for Human Biomechanics & Vestibulo-Ocular Dynamics**
 - **Structure Detection of Non-linear Systems for the Study of Human Ankle Dynamics**
- Conclusions

The Identification Problem




Identification of Stochastic or Noise Model




- Relationship between $w_1(t)$ and $z(t)$, given only system output, $z(t)$
- $u(t)$ assumed zero or constant
- Commonly known as time-series analysis
- Economic analysis, geophysical or astronomical phenomena, biological data (e.g. EKG, EEG), etc.

Identification of the Deterministic Model, \mathcal{G}



- Relationship between $u(t)$ and $y(t)$ – assumes $w_1(t) = 0$
- Input/output corrupted by noise, $e_u(t)$ & $e_z(t)$ – commonly assumes $e_u(t) = 0$
- Pursued when objective is to gain insight into the functioning of a system
- Automotive industry, chemical plants, pulp & paper, biomedical modelling (e.g. respiratory modelling, drug delivery, disease modelling, etc.)

Identification of Stochastic & Deterministic Models



- Both input/output signals available for identification
- Used when accurate predictions are desired
- Design of model-based control systems for aircraft, spacecraft or robotics.

Representation of the System \mathcal{G}

- Linear or Non-linear

- Systems in nature are inherently non-linear – especially in biology
- Linear modelling about an operating point is difficult with biological systems due to operating point variability
- Could lead to misinterpretation of physiology, e.g. disease quantification
- Biological processes should be modelled in their natural state – non-linearly

- Nonparametric or Parametric

Nonparametric Methods

- Advantage

- Provide convenient, robust means of characterising the dynamics of linear systems without requiring a priori assumptions regarding the system structure

- Disadvantage

- Nonparametric estimates of dynamics are difficult to relate to the structure and parameters of the underlying physiological system

Parametric Methods

- Disadvantage
 - Generally require a priori assumptions about the system order
- Advantage
 - Provides a concise description of the system dynamics
 - Yield results that may be related directly to the system structure

Model Form

- Linear statistical model

$$z(n) = \sum_{j=1}^p \theta_j f(\varphi_j(n)) + e(n)$$

- z : observed system output
- θ_j : unknown system parameter
- f : non-linear mapping
- φ_j : regressor
- e : independent Gaussian variable, zero-mean, σ^2 homoskedastic (constant, finite variance)

- Let φ be described as:

$$\varphi(n) = [1, u(n), \dots, u(n - n_u), z(n - 1), \dots, z(n - n_z), e(n - 1), \dots, e(n - n_e)]^T$$


- Special case f polynomial: $u^2(n-3), u(n)u(n-1), z(n-1)z(n-2), u^2(n-1)z(n-2)$
- General case f : wide variety of non-linear functions such as a sigmoid
- NARMAX

- Linear-in-the-parameters

- Linear or pseudolinear regression techniques

Example of a NARMAX Model

- Non-linear feedback model



- NARMAX representation

$$\begin{aligned}
 z(n) = & \theta_1 z(n-1) + \theta_2 z(n-2) + \theta_3 z(n-3) + \theta_4 z(n-4) + \theta_5 z^2(n-1) + \theta_6 z^2(n-2) \\
 & + \theta_7 z^2(n-3) + \theta_8 z^2(n-4) + \theta_9 z^2(n-5) + \theta_{10} u(n) + \theta_{11} u(n-1) + \theta_{12} u(n-2) \\
 & + \theta_{13} u(n-3) + \theta_{14} u(n-4) - \theta_1 e(n-1) - \theta_2 e(n-2) - \theta_3 e(n-3) - \theta_4 e(n-4) \\
 & - 2\theta_5 z(n-1)e(n-1) - 2\theta_6 z(n-2)e(n-2) - 2\theta_7 z(n-3)e(n-3) \\
 & - 2\theta_8 z(n-4)e(n-4) - 2\theta_9 z(n-5)e(n-5) + \theta_5 e^2(n-1) + \theta_6 e^2(n-2) \\
 & + \theta_7 e^2(n-3) + \theta_8 e^2(n-4) + \theta_9 e^2(n-5) + e(n)
 \end{aligned}$$

Full Identification Procedure

- Model order selection
 - Determine number of input, output and error lags and non-linearity order/basis function
- Parameter estimation
 - Determine values of unknown parameters
- Structure detection
 - Select parameters to include in model
- Model validation
 - Assess whether identified nominal model can reproduce data from a plant

Model Order

$$z(n) = f^l[1, u(n), \dots, u(n - n_u), z(n - 1), \dots, z(n - n_z), \\ e(n - 1), \dots, e(n - n_e)] + e(n)$$

- Model order represented as

$$O = [n_u \ n_z \ n_e \ l]$$

Parameter Estimation

- Need an estimate of θ using standard ℓ_2 minimisation

$$\min_{\theta} \frac{1}{2} \|(\mathbf{Z} - \Psi\theta)\|_2^2$$

- NARMAX models provide concise system representation
 - Noise on output enters model as product terms with system input and output making parameter estimation challenging

- Ordinary least-squares yields biased estimate: does not account for noise

$$\hat{\theta} = (\Psi^T \Psi)^{-1} \Psi^T \mathbf{Z} \quad \text{where} \quad \Psi = [\Psi_{zu}]$$

- Solution extended least-squares (ELS)

$$\hat{\theta} = (\Psi^T \Psi)^{-1} \Psi^T \mathbf{Z} \quad \text{where} \quad \Psi = [\Psi_{zu} \mid \Psi_{zu\hat{e}} \mid \Psi_{\hat{e}}]$$

- Bias addressed by modelling lagged errors

Structure Detection

- Selection of subset of candidate terms that best describe observed output
- Maximum number of candidate terms

$$p = \sum_{k=1}^l p_k + 1$$
$$p_k = \frac{p_{k-1}(n_z + n_u + n_e + k)}{k}, \quad p_0 = 1$$

- Example: model of order: $O = [4 \ 4 \ 4 \ 2]$
 - $p = 105$ candidate terms
 - The curse of dimensionality!
- Leads to computationally intractable combinatorial optimisation problems

Example of Candidate Terms and Structure Detection

- Model example:

$$z(n) = \theta_i u(n-1) + \theta_i u^2(n-1) + \theta_i z(n-1) + \theta_i e(n-1) + e(n)$$

- Described by: $O = [1 \ 1 \ 1 \ 2] \Rightarrow p = 15$

- Candidate terms:

$$\begin{aligned} z(n) = & \theta_0 + \theta_1 u(n) + \theta_2 u(n-1) + \theta_3 u^2(n) + \theta_4 u(n)u(n-1) + \theta_5 u^2(n-1) \\ & + \theta_6 z(n-1) + \theta_7 u(n)z(n-1) + \theta_8 u(n-1)z(n-1) + \theta_9 z^2(n-1) \\ & + \theta_{10} u(n)e(n-1) + \theta_{11} u(n-1)e(n-1) + \theta_{12} z(n-1)e(n-1) \\ & + \theta_{13} e(n-1) + \theta_{14} e^2(n-1) + e(n) \end{aligned}$$

NARMAX Representation and Identification of Ankle Dynamics


Objectives

- Theoretically derive a non-linear difference equation of a parallel pathway model of ankle dynamics
- Show that the theoretical equation for this ankle model is of the NARMAX form
- Investigate the suitability of NARMAX identification methods applied to ankle dynamics


Motivation

- Better design of prosthetics
- Characterisation of normal versus disease subjects
- Early detection of neuromuscular disease
- Design of robotic motor control systems
- Astronaut health to mitigate muscle atrophy – develop optimal exercise regime


Parallel Pathway Model of Ankle Dynamics




Parallel Pathway Model of Ankle Dynamics




Parallel Pathway Model of Ankle Dynamics




Parallel Pathway Model of Ankle Dynamics




Parallel Pathway Model of Ankle Dynamics




Parallel Pathway Model of Ankle Dynamics



Parallel Pathway Model of Ankle Dynamics



Theoretical Analysis: Linear Pathway




- Discrete-domain approximation to a derivative (Newton's backwards formula) was used to approximate the intrinsic pathway dynamics

$$s = \frac{d u(t)}{dt} \approx \frac{u(n) - u(n - 1)}{T}$$

where $T \equiv$ sampling rate and $n \equiv$ sampled data point index

Theoretical Analysis: Non-linear Pathway



- Continuous-time delay converted to discrete-time as $\tau = \lceil \frac{\Delta}{T} \rceil$ where Δ is the continuous-time delay
- Half-wave rectifier approximated as a second-order static polynomial: $c_0 + c_1x(n) + c_2x^2(n)$
 - Second-order fit accounted for over 98% of the output variance of static non-linearity
- Activation dynamics converted to discrete-time via the bilinear transform

$$s = \frac{2}{T} \left(\frac{z - 1}{z + 1} \right)$$

Theoretical Analysis: Overall Non-linear Model

- Collecting terms and combining yielded the overall non-linear model as

$$\begin{aligned} z(n) = & b_0 + b_1 z(n-1) + b_2 z(n-2) + b_3 u(n) + b_4 u(n-1) + b_5 u(n-2) \\ & + b_6 u(n-3) + b_7 u(n-4) + b_8 u(n-\tau) + b_9 u(n-\tau-1) \\ & + b_{10} u(n-\tau-2) + b_{11} u(n-\tau-3) + b_{12} u^2(n-\tau) + b_{13} u^2(n-\tau-1) \\ & + b_{14} u^2(n-\tau-2) + b_{15} u^2(n-\tau-3) + b_{16} u(n-\tau) u(n-\tau-1) \\ & + b_{17} u(n-\tau-1) u(n-\tau-2) + b_{18} u(n-\tau-2) u(n-\tau-3) \\ & + b_{19} e(n-1) + b_{20} e(n-2) + e(n) \end{aligned}$$


- This is a NARMAX model since
 - (i) it includes input-output terms that are combinations of linear, non-linear integer powers and cross-products and
 - (ii) is linear-in-the-parameters

Validation of NARMAX Ankle Model


- Simulate the NARMAX description model's response and compare it to the continuous-time model's response for typical parameter values found in experiments
- Input sequence uniformly distributed, white, zero-mean, random input, bandlimited to 30 Hz
- Operating range between ± 0.40 rad
- Sampling rate 200 Hz ($T = 0.005$ s)

Results

Parallel Pathway and NARMAX Model Input



Parallel Pathway and NARMAX Model Outputs, 99.53%VAF



Identification of NARMAX Representation of Ankle Dynamics

- Assess the utility of methods developed for identifying NARMAX models
- Noise on the output enters the model as product terms with the system input and output
- Ordinary least-squares yields biased estimate \Rightarrow Does not account for noise
- One solution extended least-squares (ELS) \Rightarrow Bias addressed by modelling lagged errors

Identification of Full NARMAX Representation Yields Biased Estimates

- Reduce number of terms
- Not a general reduction of terms to describe the data but rather a minimisation of the number of regressors or degrees of freedom used to form the regressor matrix
- Reduction provides a regressor matrix that is more stable in terms of invertibility since the coefficients will no longer be interrelated
- Similar to reconditioning a matrix via normalisation

Reduced Model Representation

- Recombining all terms according to coefficients of the static non-linearity yields an overall non-linear model represented by 12 terms as

$$\begin{aligned} z(n) = & b_0 + b_1 z(n-1) + b_2 z(n-2) + b_3 u(n) + b_4 u(n-1) + b_5 u(n-2) \\ & + b_6 u(n-3) + b_7 u(n-4) + m_1 v(n) + m_2 \chi(n) + b_{19} e(n-1) \\ & + b_{20} e(n-2) + e(n) \end{aligned}$$

where

$$v(n) = u(n-\tau) + u(n-\tau-1) - u(n-\tau-2) - u(n-\tau-3)$$



and

$$\begin{aligned} \chi(n) = & u^2(n-\tau) + 3u^2(n-\tau-1) + 3u^2(n-\tau-2) + u^2(n-\tau-3) \\ & - 2u(n-\tau)u(n-\tau-1) - 4u(n-\tau-1)u(n-\tau-2) \\ & - 2u(n-\tau-2)u(n-\tau-3) \end{aligned}$$

Experimental Data


- Eight trials of experimental human ankle data analyzed from single subject with no history of neuromuscular disease
- Pseudo-random binary sequences (PRBS) of 0.05 rad and 260 ms switching rate
- Subject maintained a mean contraction of -5 Nm

Experimental Setup




Typical Position Input and Cross-Validated Torque Output


PRBS Position Input



Measured and Cross-validated Torque, 98.84%VAF



Cross-Validation % VAF for Each Trial



Conclusions

- Non-linear difference equation describing parallel pathway model is a NARMAX model
- Simulation results show that the NARMAX model matches the continuous-time response well
- Identification methods developed for NARMAX models can be used to identify human ankle dynamics parametrically
- Experimental data shows that estimated parameters explain the input-output data well
- The NARMAX form is clearly amenable to the study of a wide range of biological systems

A Least-Squares Parameter Estimation Algorithm for Switched Hammerstein Systems With Applications to the VOR


Objectives

- Can Vestibular Ocular Reflex (VOR) be described by a NARMAX model?
- Develop identification technique to estimate parameters of non-linear hybrid (switched) systems
- Apply identification technique to experimental human VOR data

Motivation

- Characterisation of normal versus disease subjects
- Early detection and quantification of ocular disease and balance disorder
- Design of robotic motor control systems
- Pilot/astronaut health and safety

General Hammerstein Structure for Switched System




Extension of NARMAX Model for Non-Zero-Initial-State


$$z_m(n) = f_m^l[u(n), \dots, u(n - n_u)] + \mathcal{L}[z(n - 1), \dots, z(n - n_z), e(n - 1), \dots, e(n - n_e)] + e(n)$$

$$zr_m(n) = f_m^l[u(1), \dots, u(n - 1), u(n)] + \mathcal{L}[\delta(n)] \quad \text{for } m = 1, 2, \dots, \mathcal{M} \quad \forall \text{ finite } \mathcal{M}$$

Simulated VOR Data



VOR Model



$$f_1^l[U(s)] = a_1 + b_1 U(s) + c_1 U^2(s) + d_1 U^3(s) = X_1(s)$$

$$f_2^l[U(s)] = a_2 + b_2 U(s) + c_2 U^2(s) + d_2 U^3(s) = X_2(s)$$

$$Y_1(s) = \frac{K_1}{\tau_1 s + 1} X_1(s) + \frac{Y_{1i}(0)}{\tau_1 s + 1} = \frac{G_1}{s + p_1} X_1(s) + \frac{Y_{1i}(0)/\tau_1}{s + p_1}; \quad i = 1, \dots, q$$

$$Y_2(s) = \frac{K_2}{\tau_2 s + 1} X_2(s) + \frac{Y_{2\ell}(0)}{\tau_2 s + 1} = \frac{G_2}{s + p_2} X_2(s) + \frac{Y_{2\ell}(0)/\tau_2}{s + p_2}; \quad \ell = 1, \dots, r$$

NARMAX Model of VOR

- Dynamics converted to discrete-time via the bilinear transform
- Collecting terms and combining yielded an overall non-linear model with two NARMAX sub-models:

$$y(n) = \begin{cases} y_1(n) & \text{Switch Position } S_1 \\ y_2(n) & \text{Switch Position } S_2 \end{cases}$$

$$\begin{aligned} y_1(n) = & \beta_1 + \beta_2 y(n-1) + \beta_3 [u(n) + u(n-1)] \\ & + \beta_4 [u^2(n) + u^2(n-1)] + \beta_5 [u^3(n) + u^3(n-1)] \\ & + \kappa_i \delta_i(n_i); \quad i = 1, \dots, q \end{aligned}$$

$$\begin{aligned} y_2(n) = & \vartheta_1 + \vartheta_2 y(n-1) + \vartheta_3 [u(n) + u(n-1)] \\ & + \vartheta_4 [u^2(n) + u^2(n-1)] + \vartheta_5 [u^3(n) + u^3(n-1)] \\ & + \lambda_\ell \delta_\ell(n_\ell); \quad \ell = 1, \dots, r \end{aligned}$$

Biased Parameter Estimate

- Define: $\mathbf{Z} = \Psi_{zu} \hat{\boldsymbol{\theta}}_{ELS} + \boldsymbol{\xi}$
 $\boldsymbol{\xi} = \lambda_1 \delta_1(n - t_1) + \lambda_2 \delta_2(n - t_2) + \cdots + \lambda_r \delta_r(n - t_r) + e(n)$
- $E \left[\hat{\boldsymbol{\theta}}_{ELS} \right] = (\Psi^T \Psi)^{-1} \Psi^T E [\mathbf{Z}] = \hat{\boldsymbol{\theta}}_{ELS} + (\Psi^T \Psi)^{-1} \Psi^T \boldsymbol{\xi}$
- Bias: $E \left[(\Psi^T \Psi)^{-1} \Psi^T \boldsymbol{\xi} \right] \neq 0$

Modified Extended Least Squares

- Modify ELS algorithm to correct bias due to initial conditions
- Include columns in the regressor matrix to account for the initial conditions
$$\Phi = [\Psi_{zu\hat{e}} \mid \Psi_{\delta}]$$
- Extended parameter set based on this model formulation defined as:
$$\hat{\theta}_{MELS} = (\Phi^T \Phi)^{-1} \Phi^T \mathbf{Z} \quad \text{where} \quad \hat{\theta}_{MELS} = [\hat{\theta}_p \ \hat{\theta}_{\delta}].$$


Algorithm

- Segment all data according to mode
- Concatenate data from each mode
- Form regressor matrix for each mode
- Add a column modelled as an impulse when new segment is used to form the regressor matrix
- Estimate θ_{MELS} using ℓ_2 minimisation

Experimental Data

- Data analyzed from single patient with history of peripheral vestibular disease – no function in the right inner ear following surgery
 - Often associated with large non-linearity in the VOR response and abnormally small slow-phase time constant
- Experimental protocol used a sinusoidal rotation at 1/6 Hz, with a peak head velocity ~ 200 deg/s
 - Test 52 s, last 32 s recorded to measure VOR properties during sensory steady state
- Signals sampled at 500 Hz then digitally low-pass filtered to 15 Hz to reduce high frequency content

Data Analysis




$$\tilde{U}_1(s) = \frac{\tau_1 s}{\tau_1 s + 1} U(s) = \frac{s}{s + p_1} U(s) \quad \tilde{U}_2(s) = \frac{\tau_2 s}{\tau_2 s + 1} U(s) = \frac{s}{s + p_2} U(s)$$

- Canal dynamics pre-process head velocity which serve as sensor for head movement
- Sensory vestibular process well described by first-order, high-pass system which transmits signals to the central circuits acting as a switched system
- Estimate $\tau_{1,2}$ associated with vestibular dynamics, assuming $\tau_{1,2} = 1 - 15$ s in 1 s increments
 - Combination of vestibular time constant and switched system time constant which yielded highest cross-validation %QF was deemed the best-fit model
- Compared the results of MELS to ELS (not modelling initial conditions)


Experimental Setup




Experimental VOR Data




Results: Cross-Validated Eye Position




(a)



(b)




(c)



(d)

Estimated Vestibular & Switched System Parameters



Conclusions

- MELS method provides accurate estimates of parameters since it takes advantage of an entire data record even though the individual segments are short
- Results may have a clinical significance in the analysis of ocular nystagmus of all types (pursuit, optokinetic, etc.)
- Technique here allows greater insight into the functionality of various ocular reflexes, by providing quantitative measures of both saccadic and slow ocular dynamics from a single experimental record
- MELS method may be useful to estimate the coefficients of complex Hammerstein structure switched systems in biology

A Suboptimal Bootstrap Method for Structure Detection of Non-linear Output-Error Models with Application to Human Ankle Dynamics

Objectives

- Develop a structure detection method to determine a parsimonious model description which best fits the observed output
- Gain insight into the underlying process describing ankle model
- Assess whether morphological ankle model is accurate

Two Fundamental Approaches to Structure Detection

- Exhaustive search
 - Every possible subset of the full model is considered
 - Requires a large number of computations and known to not converge to true underlying system
- Parameter variance
 - Parameter variance estimates computed from model residuals
 - Often inaccurate when number of candidate terms large

Bootstrap

- Numerical procedure for estimating parameter statistics
- Mild conditions on sample errors
 - Errors independent and identically distributed (i.i.d.)
 - Zero-mean

Hypothesis

The bootstrap might be useful for structure detection of
over-parameterised non-linear models

Theoretical Analysis of Bootstrap

- Bickel and Freedman (1981) analysed linear regression model where N and p both large
- Showed for full p -dimensional distribution of least-squares estimates, bootstrap distribution will converge to true unknown distribution when

$$\gamma = \frac{p^2}{N} \rightarrow 0 \approx 0.1$$

- Initially, p cannot change; accuracy of bootstrap estimate determined by data length, N , available for estimation

Data Length

- Model order: $O = [4\ 4\ 4\ 2]$ has $p = 105$ candidate terms
- Data points: $N = \frac{105^2}{0.1} = 110,250$
- Desirable to reduce number of candidate terms

Noise Model

$$y(n) = \theta_1 y(n-4) + \theta_2 y^2(n-4) + \theta_3 u^2(n-4)y(n-4) + \theta_4 u(n-4)$$

$$z(n) = y(n) + e(n)$$

$$z(n) = \theta_1 [z(n-4) - e(n-4)] + \theta_2 [z(n-4) - e(n-4)]^2 \\ + \theta_3 u^2(n-4) [z(n-4) - e(n-4)] + \theta_4 u(n-4) + e(n)$$

- Simple output additive noise can result in complex noise model
- Number of noise terms often can be larger than process terms
- Useful to avoid estimating noise model whilst yielding a unbiased estimate
- Estimator?

Instrumental Variables

- Based on selecting instrument matrix \mathbf{V} which satisfies conditions

$$\lim_{N \rightarrow \infty} \frac{1}{N} \mathbf{V}^T \boldsymbol{\Psi}_{zu} = \mathbf{R}; \quad \text{where } \mathbf{R} \text{ is nonsingular}$$
$$\lim_{N \rightarrow \infty} \frac{1}{N} \mathbf{V}^T (\mathbf{Z} - \boldsymbol{\Psi}_{zu} \boldsymbol{\theta}_0) = 0.$$

- (i) the matrix product, $\mathbf{R} = \mathbf{V}^T \boldsymbol{\Psi}_{zu}$, has full rank, and
- (ii) the errors have zero-mean and be uncorrelated with \mathbf{V}

- This ensures the estimate

$$\hat{\boldsymbol{\theta}}_{IV} = (\mathbf{V}^T \boldsymbol{\Psi}_{zu})^{-1} \mathbf{V}^T \mathbf{Z}$$

is unbiased since the instrument matrix is not correlated with the errors

NARMAX with Linear Map

- IV gives unbiased estimates when noise represented as linear map

$$z(n) = f^l[u(n), \dots, u(n - n_u), z(n - 1), \dots, z(n - n_z)] \\ + \mathcal{L}[e(n - 1), \dots, e(n - n_e)] + e(n)$$

- Assuming output additive noise

$$z(n) = f^l[u(n), \dots, u(n - n_u)] + \mathcal{L}[z(n - 1), \dots, z(n - n_z), \\ e(n - 1), \dots, e(n - n_e)] + e(n)$$

- Restricted class of NARMAX models

- Blocked structured N-L models (static non-linearity followed by a causal, linear, time-invariant, dynamic system) such as Hammerstein models, bilinear models, etc.


Model Order & Candidate Terms

- Redefine model order as $O = [n_u \ n_z \ l]$
- Maximum number of candidate terms:

$$p = n_z + \sum_{k=1}^l p_k + 1$$
$$p_k = \frac{p_{k-1}(n_u + k)}{k}, \quad p_0 = 1$$

- Consider again earlier example: model of order: $O = [4 \ 4 \ 4 \ 2] \Rightarrow p = 105$ candidate terms
- Order redefined as $O = [4 \ 4 \ 2] \Rightarrow p = 25$ terms need be considered; a significant reduction

Parallel Pathway Model of Ankle Dynamics Revisited



Overall Non-linear Model of Ankle Dynamics

$$\begin{aligned} z(n) = & b_0 + b_1 z(n-1) + b_2 z(n-2) + b_3 u(n) + b_4 u(n-1) + b_5 u(n-2) \\ & + b_6 u(n-3) + b_7 u(n-4) + b_8 u(n-\tau) + b_9 u(n-\tau-1) \\ & + b_{10} u(n-\tau-2) + b_{11} u(n-\tau-3) + b_{12} u^2(n-\tau) + b_{13} u^2(n-\tau-1) \\ & + b_{14} u^2(n-\tau-2) + b_{15} u^2(n-\tau-3) + b_{16} u(n-\tau) u(n-\tau-1) \\ & + b_{17} u(n-\tau-1) u(n-\tau-2) + b_{18} u(n-\tau-2) u(n-\tau-3) \\ & + b_{19} e(n-1) + b_{20} e(n-2) + e(n) \end{aligned}$$

- Reflex delay 50-100 ms; corresponding to a discrete-time delay $\tau = \lceil \frac{\Delta}{T} \rceil$
 - Maximum model order $O = [8 \ 2 \ 2 \ 2]$
- Gives full model description with 105 candidate terms
 - True system described by 21 parameters
- Computationally intractable combinatorial optimisation problem

Overall Non-linear Model of Ankle Dynamics

$$\begin{aligned} z(n) = & b_0 + b_1 z(n-1) + b_2 z(n-2) + b_3 u(n) + b_4 u(n-1) + b_5 u(n-2) \\ & + b_6 u(n-3) + b_7 u(n-4) + b_8 u(n-\tau) + b_9 u(n-\tau-1) \\ & + b_{10} u(n-\tau-2) + b_{11} u(n-\tau-3) + b_{12} u^2(n-\tau) + b_{13} u^2(n-\tau-1) \\ & + b_{14} u^2(n-\tau-2) + b_{15} u^2(n-\tau-3) + b_{16} u(n-\tau) u(n-\tau-1) \\ & + b_{17} u(n-\tau-1) u(n-\tau-2) + b_{18} u(n-\tau-2) u(n-\tau-3) \\ & \textcolor{red}{+ b_{19} e(n-1) + b_{20} e(n-2)} + e(n) \end{aligned}$$

- Reflex delay 50-100 ms; corresponding to a discrete-time delay $\tau = \left\lceil \frac{\Delta}{T} \right\rceil$
 - Maximum model order $O = [8 \ 2 \ 2 \ 2]$
- Use *a priori* knowledge to eliminate unrealistic candidate terms, increasing computational efficiency
 - Eliminate all nonlinear and cross-terms associated with discrete-time delays between $\tau = [0 \ 2]$
- Gives full model description with 33 candidate terms
 - True system described by 19 parameters
- Computationally *tractable* combinatorial optimisation problem


Assumptions

- System order assumed known
 - Small signal perturbations to estimate a LTI model order
- SOBSD algorithm limits possible class of models but it is reasonable to consider this limited set since the physical model suggests that the true system lies within this class
- Structure detection provide useful process insights that can be used in subsequent development or refinement of physical models


Experimental Data

- Data analysed two data sets from a subject with no history of neuromuscular disease
- PRBS input with 0.06 rad peak-to-peak amplitude and switching rate of 125 ms and 260 ms whilst subject maintained a mean contraction of -5 Nm
- Input-output recorded for 50 seconds
- Measured data sampled at 500 Hz, for estimation data decimated to 50 Hz
- Estimation data $N_e = 2,000$, validation data $N_v = 1,000$ and $B = 100$ bootstrap replications to estimate parameter statistics

Results of Identifying Experimental Human Ankle Data Set 1



Results of Identifying Experimental Human Ankle Data Set 2



Conclusions

- SOBSD algorithm provides a novel approach to the model selection problem without computing a noise model and, hence, reducing the dimensionality of this ill-posed combinatorial optimisation problem
- Reduction in dimensionality comes at cost of limited model structures that can be considered
- Study illustrates usefulness of structure detection as an approach to validate morphological models via analysis of input-output data
- Results show identified model structure matches the theoretically expected structure well
- Indicates morphological modeling studies may be accurate for this model describing ankle dynamics

Acknowledgments

Supported by grants from the Natural Sciences Engineering Research Council of Canada, the Canadian Institutes for Health Research, the Max Stern Fellowship of McGill University and Vetenskapsrådet, The Swedish Research Council